JIANGHAC
GENERATOR

Genset	
Model	JHM-1600GF
Voltage	277/480V
Frequency&Speed	60HZ;1800RPM
Genset Prime Power	1600kW/2000kVA
Genset Standby Power	1750kW/2188kVA

CE

Name	12V4000G83S		
Application Group	3G		
Dataset	Ref. 25°C/55°C		

Engine: MTU 12V4000G83S

Alternator:Stamford/Leroy Somer

/Hengsheng

Controller:DeepSea/SmartGen

/DEIF/ComAp

Speed [rpm]	1800
Nominal power [kW]	1736
Nominal power [bhp]	2328
Nominal power [kVA]	-
Nominal power [kWel]	1
Frequency [Hz]	60

Exhaust Regulations Fuel-consumption optimized;

Reference conditions

No.	Description	Index	Value	Unit
6	Intake air temperature	_	25	°C
7	Charge-air coolant temperature		55	°C
8	Barometric pressure	0.00 0	1000	mbar
9	Site altitude above sea level		100	m
1	Engine rated speed	A	1800	rpm
2	Reduction gear - Output speed	A	-	rpm
3	Mean piston speed		12.6	m/s
4	Continuous power ISO 3046 (10% overload capability) (design power DIN 6280, ISO 8528)	A	1736	kW
5	Fuel stop power ISO 3046	A	1910	kW
8	Mean effective pressure (MEP) (Continuous power ISO 3046)		20.2	bar
9	Mean effective pressure (MEP) (Fuel stop power ISO 3046)		22.3	bar
1	Intake air depression (new filter)	A	15	mbar
2	Intake air depression, max.	L	50	mbar
3	Exhaust back pressure	A	30	mbar
4	Exhaust back pressure, max.	L	85	mbar
5	Fuel temperature at fuel feed connection	R	25	°C
9	Fuel temperature at fuel feed connection, max. (w/o power reduction)	L	55	°C
10	Fuel temperature at fuel feed connection, max.	Ĺ	55	°C
_				



No.	Description	Index	Value	Unit
17	Specific fuel consumption (be) - 100 % CP (+ 5 %; EN 590; 42.8 MJ/kg)	R	200	g/kWh
18	Specific fuel consumption (be) - 75 % CP (+ 5 %; EN 590; 42.8 MJ/kg)	R	198	g/kWh
19	Specific fuel consumption (be) - 50 % CP (+ 5 %; EN 590; 42.8 MJ/kg)	R	211	g/kWh
20	Specific fuel consumption (be) - 25 % CP (+ 5 %; EN 590; 42.8 MJ/kg)	R	244	g/kWh
21	Specific fuel consumption (be) - FSP (+ 5 %; EN 590; 42.8 MJ/kg)	R	206	g/kWh
6	Number of cylinders		12	-
7	Cylinder configuration: V angle	1	90	degrees (°)
8	Cylinder configuration: in-line vertical	1	-0	-
10	Bore		170	mm
11	Stroke		210	mm
12	Displacement, cylinder		4.77	liter
13	Displacement, total		57.2	liter
14	Compression ratio		16.4	5
28	Standard flywheel housing flange (engine main PTO)		00	SAE
50	Static bending moment at standard flywheel housing flange, max.	L	15	kNm
51	Dynamic bending moment at standard flywheel housing flange, max.	L	75	kNm
29	Standard flywheel housing flange (reduction gearbox main PTO)		-	SAE
43	Flywheel interface (DISC)		21	-

Alternator

Pole No.	4-Pole		
Exciter Type	Single bearing, Brushless, Self-excited	♦	NEMAMG1.JIANGHAO,
			standards compliance f
Power factor	0.8		temperature rise and m
Voltage adjust range	≦5%	\diamond	Sustained short-circuit
Insulation Grade	Н		to 300% of the rated cu
Protection Grade	IP23/22		10 seconds.
Phase / wire	3 phase 4 wires	\diamond	Sustained short-circuit
			enabling down stream

- ∻ Superior voltage waveform from two-thirds Pitch windings and skewed stator.
- ∻ Digital solid-state.volts-per-hertz voltage Regulator with +1% no-load to full-load regulation.

- ,and ANSI for motor starting.
- current of up current for up to
- current circuit breakers to trip without collapsing the generator field.
- ∻ Self-ventilated and dripproof construction.



Control Panel



The control module gives digital readouts of: Generator voltage; Output frequency; Engine speed; Battery voltage;

Engine hours run.



Dimension:6100*2200*2710mm Weight:13000kg



Dimension:12000*2400*2900mm Weight:16800kg Fuel Tank Capacity:1000-3000L The **control panel** is an Digital Control Module suitable for a wide variety of single, diesel or gas, gen-set applications.

Monitoring an extensive number of engine parameters, the module will display warnings, shutdown and engine status information on the back-lit LCD screen and illuminated LEDs.

The control module has indicators for failure information:

Over speed/Low speed, Emergency stop Low oil pressure; High water temperature Failure to start Battery charger failure

Automatic shutdown occurs under:

Low engine oil pressure; High engine water temperature; Over speed/Low speed; Failure to start after three attempts.

Electrical system

- Maintenance-free and anti-explosion battery
- Standard breaker
- ABB breaker (optional)
- ATS (optional)
- Battery charger (optional)
- GMS monitoring (optional)

Packing

- Wrapping film packaging
- Tray packaging
- plywood box packaging

Jiangsu Jianghao Generator Co.,Ltd

Address: No.1 Xixu Road, Medical High-tech Zone,

Taizhou city, Jiangsu, China Contact Person: Anthony Feng Email: <u>ihfsale@jhgenerator.com</u> WhatsAPP: +86 18652649673

